

HFC 7 ways return path optical receiver, 1
way reverse optical transmitter

- HR2071A, HR2071B Series

Technical Specification

CONTENT

1.0	PRODUCT DESCRIPTION	1
2.0	FEATURES AND BENEFITS	2
3.0	MAIN APPLICATION	2
4.0	TECHNICAL INDEX	3
4.1	UP-STREAM OPTICAL RECEIVER.....	3
4.2	UP-STREAM OPTICAL TRANSMITTER.....	4
5.0	ORDER INFORMATION	5
5.1	UP-STREAM OPTICAL RECEIVER.....	5
5.2	UP-STREAM OPTICAL TRANSMITTER.....	5

1.0 PRODUCT DESCRIPTION

HR2071 series of HFC seven-way return path receiver, one way reverse optical transmitter, mainly used at the head-end to convert upstream optical signal to RF signal at the user side. Moreover, send back the data at sub-HE to main head-end through one way of DFB return path transmitter. Eight independent units integrated into a 1RU 19" casing to provide service for HFC network terminal of ONTs. The receivers' low noise design of -22dBm receive sensitivity, allow to supply service to farther distance.

There are two versions of this receiver. HR2071A with LCD on the front panel, HR2080B without LCD. All receivers are temperature tolerance type can be installed in any network surroundings including out-door type. Both of these two types can adopt SNMP function, which can control the front panel to realize optimization work at the head-end and remote installment.

2.0 Features and benefits

- 7 low noise optical receiver, up to -22dBm receive sensitivity
- One way return path transmitter can send back the data at sub-front-end to main front-end
- 1200~1620nm band wavelength
- SNMP network management function option
- RF output level can be adjusted by network
- Built-in 1+1 backup power, redundant A/B inputs (option)
- Good performance of resistance to temperature, allow -40~+65 °C operating temperature
- Simple mode, high density, 19" 1RU mount, contain 8 pcs of independent optical receiver and optical transmitter
- Excellent P/P ratio

3.0 Main application

- HFC network sub-head

4.0 TECHNICAL INDEX

4.1 Up-stream optical receiver

Performance			Index			Supplement		
			Min.	Typ.	Max.			
Optic feature	Operating wavelength (λ)		(nm)	1200		1620		
	Responsivity	R13	(A/W)	0.85	0.95		1310nm	
		R15		0.85	1.0		1550nm	
		R16			0.85		1610nm	
	Optical link budget loss		(dB)	17				
	Receiving power	Typical		(dBm)	-17		-7	
		Sensitivity				-23	-22	Pr
		Overload			0	+1		Po
	Number of optical receiver		(pcs)	7				
	Return loss		(dB)	50				
Optical connector			SC/APC			LC/APC option		
RF feature	Operating bandwidth		(MHz)	5		200		
	RF output level		(dBmV)	30		60		
	RF gain adjustable		(dB)	-30		0	Settable=1dB	
	Flatness		(dB)	-0.75		+0.75		
	Return loss		(dB)	16				
	RF test point/monitor		(dB)	-20.5	-20	-19.5		
	Noise power ratio		(dB)	41			Link loss>15dB	
General feature	Power supply	AC	(V)	90	220	265		
		DC		-30	-48	-72		
	Power consume		(W)			96		
	Operating temp.		(°C)	-40		+65		
	Relative humidity		(%)	5		95		
Size		(")	19×12×1.75			(W)×(D)×(H)		

4.2 Up-stream optical transmitter

Performance			Index			Supplement
			Min.	Typ.	Max.	
Optical feature	Reverse transmitter operating wavelength (λ)	(nm)		1310		
				1550		
				1470		CWDM 1470
				1490		CWDM 1490
				1510		CWDM 1510
				1530		CWDM 1530
				1550		CWDM 1550
				1570		CWDM 1570
				1590		CWDM 1590
				1610		CWDM 1610
Type of laser with return path			DFB without ISO			DFO
			DFB with ISO			DFI
Output power		(mW)	1.2			1dBm
			2			3dBm
			2.5			4dBm
			3			5dBm
Return loss	(dB)	50				
Output power monitor	(V/mW)		1			
Connector			SC/APC			
RF feature	Operating bandwidth	(MHz)	5		30	Duplexer 30/47
					42	Duplexer 42/53
					65	Duplexer 65/87
	Flatness	(dB)	-0.5		+0.5	5~65MHz
	Noise Power Ratio (NPR)	(dB)	41			Link Loss \geq 15dB
	Input level	(dBmV)		20		
	Return loss	(dB)	16	18		5~65MHz
Input power monitor	(dB)		20			

5.0 Order information

5.1 Up-stream optical receiver

HR 2 0 8 0 A - W F F - S A □ □

In-door CATV optical receiver	Bandwidth		Reception sensitivity		Number of optical receiver		Number of optical transmitter		Whether has LCD on the front panel		Network management		RF output port position		Optical port position		Connetor		Power supply	
	1	2	0	-22dBm	4	4 pcs	0	None	A	With LCD	N	No	F	Front panel	F	Front panel	SA	SC/APC	22	220VAC
	2	200MHz	1	-32dBm	7	7 pcs	1	1 pcs	B	Without LCD	W	With	B	Back panel	B	Back panel	FA	FC/APC	11	110VAC
	7	750MHz			8	8 pcs											LA	LC/APC	48	-48VDC
	8	870MHz																		
	9	1000MHz																		

5.2 Up-stream optical transmitter

□ □ □ □ - □ □ □ □

Output power		Type of laser with return path		Operating wavelength	
1	1dBm, 1.2mW	DFO	DFB without ISO	1310	1310nm
3	3dBm, 2.0mW	DFI	DFB with ISO	1550	1550nm
4	4dBm, 2.5mW			1470	CWDM 1470nm
5	5dBm, 3.0mW			1490	CWDM 1490nm
				1510	CWDM 1510nm
				1530	CWDM 1530nm
				1550	CWDM 1550nm
				1570	CWDM 1570nm
				1590	CWDM 1590nm
				1610	CWDM 1610nm

Hangzhou Huatai Optic Tech. CO., LTD

www.catvworld.net

E-mail: ht@catvworld.net